

Federal Communications Commission

§ 95.669

supervision and responsibility of a person certified as technically qualified to perform transmitter maintenance and repair duties in the private land mobile services and fixed services by an organization or committee representative of users of those services.

(3) Warnings concerning the replacement of any transmitter component (crystal, semiconductor, etc.) that could result in a violation of the rules.

(4) For a CMRS transmitter, warnings concerning licensing requirements and information concerning license application procedures.

[53 FR 36789, Sept. 22, 1988. Redesignated at 61 FR 28769, June 6, 1996, and further redesignated at 61 FR 46567, Sept. 4, 1996]

EFFECTIVE DATE NOTE: At 61 FR 46567, Sept. 4, 1996, §95.653 was redesignated as §95.655 and new §95.653 was redesignated from §95.651, effective Oct. 4, 1996.

§95.655 Frequency capability.

(a) No transmitter will be type accepted for use in the CB service if it is equipped with a frequency capability not listed in §95.625, and no transmitter will be type accepted for use in the GMRS if it is equipped with a frequency capability not listed in §95.621, unless such transmitter is also type accepted for use in another radio service for which the frequency is authorized and for which type acceptance is also required. (Transmitters with frequency capability for the Amateur Radio Services, Military Affiliate Radio System and Civil Air Patrol will not be type accepted.)

(b) All frequency determining circuitry (including crystals) and programming controls in each CB transmitter and in each GMRS transmitter must be internal to the transmitter and must not be accessible from the exterior of the transmitter operating panel or from the exterior of the transmitter enclosure.

(c) No add-on device, whether internal or external, the function of which is to extend the transmitting frequency capability of a CB transmitter beyond its original capability, shall be manufactured, sold or attached to any CB station transmitter.

[53 FR 47718, Nov. 25, 1988. Redesignated at 61 FR 28769, June 6, 1996, and further redesignated at 61 FR 46567, Sept. 4, 1996]

EFFECTIVE DATE NOTE: At 61 FR 46567, Sept. 4, 1996, §95.655 was redesignated from §95.653, effective Oct. 4, 1996.

ADDITIONAL TYPE ACCEPTANCE REQUIREMENTS FOR CB TRANSMITTERS

§95.665 [Reserved]

§95.667 CB transmitter power.

The dissipation rating of all the semiconductors or electron tubes which supply RF power to the antenna terminals of each CB transmitter must not exceed 10 W. For semiconductors, the dissipation rating is the greater of the collector or device dissipation value established by the manufacturer of the semiconductor. These values may be temperature de-rated by no more than 50° C. For an electron tube, the dissipation rating is the Intermit-tent Commercial and Amateur Service plate dissipation value established by the manufacturer of the electron tube.

[53 FR 36789, Sept. 22, 1988. Redesignated at 61 FR 28769, June 6, 1996, and further redesignated at 61 FR 46567, Sept. 4, 1996]

EFFECTIVE DATE NOTE: At 61 FR 46567, Sept. 4, 1996, §95.667 was redesignated as §95.669 and new §95.667 was redesignated from §95.665, effective Oct. 4, 1996.

§95.669 External controls.

(a) Only the following external transmitter controls, connections or devices will normally be permitted in a CB transmitter:

(1) Primary power connection. (Circuitry or devices such as rectifiers, transformers, or inverters which provide the nominal rated transmitter primary supply voltage may be used without voiding the transmitter type acceptance.)

(2) Microphone connection.

(3) Antenna terminals.

(4) Audio frequency power amplifier output connector and selector switch.

(5) On-off switch for primary power to transmitter. This switch may be combined with receiver controls such as the receiver on-off switch and volume control.

(6) Upper/lower sideband selector switch (for a transmitter that transmits emission type H3E, J3E or R3E).

(7) Carrier level selector control (for a transmitter that transmits emission type H3E, J3E or R3E.) This control